

## QPhase™ Encoders

### **QR110**

#### **DESIGN FEATURES**

- Standard size 11 encoder mounting
- Compatible with size 11 resolver mounting
- Resolutions up to 2048 PPR direct read
- · Unique optical sensing system
- · Differential and single ended outputs
- Nickel coated carbon fiber composite housing
- IP50 sealing
- · High noise immunity
- RoHS Construction
- Low supply current requirements



Quantum Devices, Inc. Model QR110 is designed to provide high resolution digital feedback in an industrial standard size 11 mounting format. Quadrature with reference pulse output format, resolutions up to 2048 lines per revolution (direct read) and a variety of electrical options are easily capable of satisfying the most demanding feedback application. The QR110 provides the user digital position information, directly from the feedback device, without the external R to D converters that are typically used with resolver feedback. Converting from size 11 resolver to encoder feedback is easily accomplished with the QR110 without the need for costly mounting modification to existing designs. QDI's unique optical sensing system embodies a much simplified encoder design, which ultimately results in longer service life and less downtime due to feedback device failure. The encoder housing is constructed of a conductive carbon fiber composite that provides the EMI shielding of an all-metal housing and performance of a lightweight robust assembly.



#### **Configuration Options:**

112 Orbison St., P.O. Box 100

Barneveld, WI 53507 (608) 924-3000 qdisales@quantumdev.com

Quantum Devices, Inc.

#### Voltage Resolution 05/05 = 5 VDC

500, 512, 05/26 = 5-26 VDC 1000, 1024 2000, 2048

#### Output 01 = TTL


02 = Line Driver 03 = 5-26 VDC Line Driver

#### I/O Termination

01 = Straight Pins 02 = 8" Ribbon Cable w/Connector Solid Shaft S1 = 0.125"



# **OUTPUT WAVEFORMS**




Viewed From Shaft End

**OUTPUT CIRCUITS** 

#### **ELECTRICAL SPECIFICATIONS** 5 VDC ± 5% or 5-26 VDC Input Voltage Input Current Requirements 80 mA max. Output option 01 & 02, 35 mA max output option 03; plus interface loads Input Ripple 2% peak to peak @ 5 VDC 01 = TTL output (single-ended) **Output Circuits** 02 = 26C31 line driver (RS-422) 03 = OL7272 high voltage line driver Quadrature with A leading B for CW rotation **Output Format** Ungated Z index pulse true over A and B high Max Operating Frequency 200 kHz 180° electrical ± 10% Symmetry Minimum Edge Separation 54° electrical

Outputs A, B & Z TTL Output




Outputs A', B' & Z' 26C31 line driver (RS-422) OL7272 5-26 V line driver


ENVIRONMENTAL SPECIFICATIONS		
Storage Temperature	-40 to 125°C	
Operating Temperature	0 to 70°C typical -20 to 100°C optional**	
Humidity	98% non-condensing	
Vibration	20 g's @ 50 to 500 CPS	
Shock	50 g's @ 11 ms duration	


MECHANICAL SPECIFICATIONS		
Maximum Shaft Speed	8000 RPM	
Nominal Shaft Diameter	0.125"	
Shaft Material	Stainless steel	
Bearings	Radial ball bearing, R2 type	
Radial Shaft Load	2 lb maximum	
Axial Shaft Load	1 lb maximum	
Housing	Carbon fiber composite (case ground via connector)	
Housing Volume Resistivity	10 <sup>-2</sup> ohm•cm	
Termination	Two rows of 5 pins on 0.100" centers 8" ten conductor ribbon cable with 2x5 connector	
Mounting	Size 11 resolver	
Moment of Inertia	9.5x10 <sup>-6</sup> oz·in·s <sup>2</sup>	
Acceleration	1x10 <sup>5</sup> radians/s <sup>2</sup>	

QR110 WIRING INFORMATION		
Pin Number	Function	
1	Common	
2	Vcc	
3	Z	
4	Z′	
5	В	
6	B′	
7	Α	
8	A´	
9	NC	
10	Case	

Maximum Shaft Speed	8000 RPM
Nominal Shaft Diameter	0.125"
Shaft Material	Stainless steel
Bearings	Radial ball bearing, R2 type
Radial Shaft Load	2 lb maximum
Axial Shaft Load	1 lb maximum
Housing	Carbon fiber composite (case ground via connector)
Housing Volume Resistivity	10 <sup>-2</sup> ohm∙cm
Termination	Two rows of 5 pins on 0.100" centers 8" ten conductor ribbon cable with 2x5 connector
Mounting	Size 11 resolver
Moment of Inertia	9.5x10 <sup>-6</sup> oz·in·s <sup>2</sup>
Acceleration	1x10 <sup>5</sup> radians/s <sup>2</sup>
	**C







\*Quantum Devices, Inc. reserves the right to make changes in design, specifications and other information at any time without prior notice.

REV. 200601

